

	Preset mode 0~37	For example: #preset mode5 exe=2 calling mode 5
Seamless Matrix	0:P2P 1:All outputs switch to input 1 2:All outputs switch to input 2 3:All outputs switch to input 3 4:All outputs switch to input 4 5:All outputs switch to input 5 6:All outputs switch to input 6 7:All outputs switch to input 7 8:All outputs switch to input 8 9:All outputs switch to input 9	
	10: 1 input 3x3 video wall	
	11:3×2 U	
	12:3×2 D	
	13:2×2 LU	
	14:2×2 RU	


15:2×2 LD



16:2×2 RD



17:3×1 L




Video Wall

18:1×3 L



19:3×1 3×2



20:1×3 2×3



21:3×1U 2×2L



22:1×3L 2×2U



23:3×1×3



24:1×3×3



25:1×3 2×1×3




26:1×2×3 3×1



27: 3x3 Grid-1

1	2	3
4	5	6
7	8	9

28: PIP 1



29: 2x2 Grid-1

1	2
3	4

30: 2x2 Grid-2

5	6
7	8

31: 2x3 Grid-1

1	2	3
4	5	6

Multi-Viewer 32: 2x3 Grid-2

1	2	3
7	8	9

33: 2x3 Grid-3

4	5	6
7	8	9

34: 2Main-6small

1			2		
4	5	6	7	8	9

35: 1main-5small

1					2
4	5	6	7	8	

36: 1mian-5small

1				4
				5
				6
				7
				8

37: 1mian-7small

1			2
			3
			4
9	8	7	5

	Head of commands	parameter 1	parameter 2	parameter 3	property parameter (only use for parameter 2)	property parameter (only use for parameter 3)
Audio	#audio_%c	dec=%d	out%d	in%d	onoff=%d	delay=%d
	d:operating parameter	0: off	0: All output	0:All input	0:off audio	0~50: support 0~50
		1~x: Specified output audio	1-x:Specified output	1-x:Specified input	1:on audio	51: auto

Example: #audio_d out0 onoff=0 close all outputs audio

	Head of commands	parameter 1	parameter 2	property parameter
EDID	#edid_%c	in%d	user%d	source=%d
	d:operating parameter	0:ALL input	0: all user	0~3:default
		1-x:specified input	1-x:specified user	4~7:user
				8~16:output
				17:temp

Example:#edid_d in1 source=2 Set EDID of inpu1 to Default 3

	Head of commands	property parameter	property parameter	property parameter
LCD	#lcd	shut=%d	level=%d	main=%d
		0-255:Screen off time	0-8:Backlight level	0-255:How many seconds will it take to return to the main interface

Example: #lcd shut=20 level=7 main=30 Set the screen-off time of the LCD screen to 20 seconds, the backlight level to 7, and return to the main interface after 30 seconds of operation

	Head of commands	parameter 1	parameter 2	property parameter
preset	#preset	mode%d	scene%d	exe=%d
		0~37: specified mode	0~7: specified scene	0:clear
				1:save
				2:call

Example: #preset mode5 exe=2 Call mode 5

	Head of commands	property parameter	property parameter
register	#register%d	id=%15t	psd=%15t
account	0-4:register account level	Digits, letters, and underscores: user name	Digits, letters, and underscores: password

Example: #register1 id=abcdef psd=abcdef register level 1 account, account and password is abcdef

login account	Head of commands	property parameter	property parameter
	#login	id=%15t Digits, letters, and underscores: user name	psd=%15t Digits, letters, and underscores: password

example: #login id=admin psd=admin login account(account and password is admin)

Name change	Head of commands	parameter 1	parameter 2	parameter 3	property parameter
	#name	input%d 0:ALL output 1-x:specified output	output%d 0:ALL output 1-x:specified output	scene%d 0-x:specified scene	str=%15v Visible string: Port name

example: #name input1 str=123 Set name of input 1 to 123

power	Head of commands	property parameter	property parameter
	#power	shut=%d 0 :cancel timed shutdown 1-x :time of timed shutdown, unit/second Endless :Longer than 7*24*3600 seconds	start=%d 0 :cancel timed start 1-x :time of timed start, unit/second Endless :Longer than 7*24*3600 seconds

example: #power shut=10 start=20 Set 10seconds scheduled shutdown and 20seconds scheduled start

IP setting	Head of commands	property parameter	property parameter	property parameter	property parameter	property parameter
	#network	ip=%d.%d.%d.%d 0-255:ip address	mask=%d.%d.%d.%d 0-255:Mask address	gw=%d.%d.%d.%d 0-255:Gateway address	dns=%d.%d.%d.%d 0-255:DNS address	dhcp=%d 0:off DHCP 1:on DHCP

example: #network ip=192.168.1.167 mask=255.255.255.255 gw=255.255.255.255 dns=255.255.255.255 dhcp=0

system	Head of commands	property parameter	property parameter	property parameter	property parameter	property parameter	property parameter
	#system	company=%1,31r Visible string: Change the company name	type=%1,31r Visible string: Change the product model	versions=%1,31r Visible string: Change the release version number	web=%1,31r Visible string: Change the company URL	email=%1,31r Visible string: change the email address	tel=%1,31r Visible string: change the contact number

example: #system company=XXX type=HHH Set company name to XXX, product model to HHH

Head of commands		parameter 1	property parameter	property parameter
#video_d		out%d	matrix=%d	format=%d
video switich	matrix mode			0-7: output resolution
				include
				4k60, 4k30,1080p60, 72
		0:ALL output		0p60, 2560×1600
		1-x:specified output	1-x: switch	60, 1920×1200
				60, 1600×1200
				60, 1366×768 60
				57: follow output

example: #video_d out0 matrix=1 format=0 Set all output switch to input 1, resolution to 4K60